


ProTalk Cv3


Firmware Update Tutorial

The Cv3 Firmware Update Tutorial will walk you through the steps needed to update your Cv3 to the latest firmware revision. Before you begin, make sure that the latest ProTalk Cv3 Database Editor (programming software) has been installed on your PC (<http://barnett-engg.com/support/Software.aspx>). The latest Cv3 .upg file needs to be downloaded from our website as well (http://barnett-engg.com/support/Firmware_Updates.aspx). There are 3 upgrade files to choose from. Select the file that corresponds to the Cv3 hardware version (as seen on the label on the side of the unit beside: VERSION).


Apply power to the Cv3, connect the program cable (USB/DB9) and open the programming software:




Under the 'File' heading, select 'Update Module Firmware.' The following window appears:




Press the 'Next' button:



Press 'Next' again:




Select the appropriate COM port in the drop-down-box (the port will already be selected if a USB cable is used):




ProTalk Cv3

Firmware Update Tutorial

Press 'Next' twice to place the Cv3 into update mode:




Press 'Open' and select .upg file from the location it was saved to earlier:




Press 'Next' and the transfer will begin:





Once the file transfer has completed, a 'Success!!' message appears:



The Cv3 will automatically restart. Close the window and exit the program. The update is complete.